

Surface code quantum communication

Austin G. Fowler¹, David S. Wang¹, Charles D. Hill¹, Thaddeus

D. Ladd^{2,3}, Rodney Van Meter⁴, Lloyd C. L. Hollenberg¹

¹*Centre for Quantum Computer Technology, University of Melbourne, Victoria, Australia*

²*Edward L. Ginzton Laboratory, Stanford University, Stanford, CA, 94305-4088, USA*

³*National Institute of Informatics, 2-1-2 Hitotsubashi, Chiyoda-ku, Tokyo-to 101-8430, Japan*

⁴*Faculty of Environment and Information Studies, Keio University,
5322 Endo, Fujisawa, Kanagawa, 252-8520, Japan*

(Dated: February 5, 2010)

Quantum communication typically involves a linear chain of repeater stations, each capable of reliable local quantum computation and connected to their nearest neighbors by unreliable communication links. The communication rate in existing protocols is low as two-way classical communication is used. We show that, if Bell pairs are generated between neighboring stations with a probability of heralded success greater than 0.65 and fidelity greater than 0.96, two-way classical communication can be entirely avoided and quantum information can be sent over arbitrary distances with arbitrarily low error at a rate limited only by the local gate speed. The number of qubits per repeater scales logarithmically with the communication distance. If the probability of heralded success is less than 0.65 and Bell pairs between neighboring stations with fidelity no less than 0.92 are generated only every T_B seconds, the logarithmic resource scaling remains and the communication rate through N links is proportional to $(T_B \log^2 N)^{-1}$.

Long-range communication of quantum states is difficult as such states cannot be copied [1, 2]. Current research into long-range quantum communication focuses on quantum repeaters [3] making use of entanglement purification [4] and entanglement swapping [5, 6]. Entanglement purification requires slow two-way classical communication, resulting in the quantum communication rate decreasing polynomially with distance. Furthermore, the communication error rate p_c is at best comparable to the error rate p_g of gates within repeaters. If qubits have a finite coherence time, requesting a constant p_c as the distance increases results in a finite maximum communication distance. Arbitrarily rapid and reliable communication over arbitrary distances is not possible using only entanglement purification and swapping.

Initial work incorporating error correction into quantum communication resulted in non-fault-tolerant schemes [7, 8] capable of reliably correcting only a small, fixed number of errors. Recently, the first steps towards fault-tolerant quantum communication were taken [9], however entanglement purification was still used between neighboring quantum repeaters, fundamentally limiting the communication rate to hundreds of logical qubits per second. A quantum communication protocol requiring very little two-way classical communication has been developed concurrent with this work [10]

We show that, using surface code quantum error correction [11–14], two-way classical communication can be avoided entirely provided we can create Bell pairs between neighboring stations with a heralded success probability $S_B \gtrsim 0.65$ and fidelity $F \gtrsim 0.96$. This means communication can proceed at a rate independent of the classical communication time between repeater stations. Given local quantum gates with $p_g \ll 0.75\%$, we show that it is possible to communicate logical qubits over ar-

bitrary distances with arbitrarily low p_c at a rate limited only by the local gate speed. The number of qubits per repeater increases only logarithmically and the quantum communication rate decreases only logarithmically with communication distance.

To describe our quantum communication protocol, we must first describe surface codes and this in turn requires the notion of stabilizers [15]. A stabilizer of $|\Psi\rangle$ is an operator M such that $M|\Psi\rangle = |\Psi\rangle$. For example, $Z|0\rangle = |0\rangle$. Given any set of commuting operators $\{M_i\}$, a state $|\Psi\rangle$ exists stabilized by $\{M_i\}$.

Surface codes can be defined on lattices of the form shown in Fig. 1. Data qubits are represented by open circles. We define a set of commuting operators on data qubits by associating $ZZZZ/XXXX$ with each face/vertex. If the $|\Psi\rangle$ stabilized by these operators suffers errors, becoming $|\bar{\Psi}\rangle$, then local to these errors we obtain equations of the form $M|\bar{\Psi}\rangle = -|\bar{\Psi}\rangle$. Measuring whether the qubits are in the $+1$ or -1 eigenstate of each stabilizer thus gives us information about the errors in the lattice. Measuring a stabilizer requires a sequence of six gates. This information can be used to reliably correct the errors provided the error rates of initialization, CNOT, measurement, and memory, which here we take to be equal at rate p_g , are all less than approximately 0.75% [13, 14, 16]. Logical operators X_L/Z_L are chains of single-qubit X/Z operators that commute with every Z/X stabilizer and link the top/left boundary to the bottom/right. The distance d of the code is the number of single-qubit operators in the shortest logical operator.

Transmitting surface code logical qubits is of particular interest as the surface code possesses a high threshold error rate, requires only local interactions, is highly tolerant of defective qubits [17] and permits fast, arbitrarily long-range logical CNOT — a collection of properties no




FIG. 1: A surface code logical qubit. Stabilizers $ZZZZ/XXXX$ are associated with the data qubits (open circles) around each face/vertex. Syndrome qubits (dots) measure stabilizers using the indicated sequences of gates. Logical operators Z_L, X_L connect opposing boundaries.

other scheme currently possesses. There are a number of proposed architectures well-suited to implementing the surface code [18–20].

We now describe our communication protocol, initially restricting ourselves to moving a logical qubit from the left end to the right end of a single monolithic array of qubits with the ability to perform local gates. Given an arbitrary surface code logical qubit $|\Psi_L\rangle$ at the left end of the array, an uninitialized region of qubits $|\Psi\rangle$ in the middle and a surface code logical qubit $|0_L\rangle$ at the right end, $|\Psi_L\rangle$ can be fault-tolerantly teleported to the location of $|0_L\rangle$. First, the uninitialized region is measured as shown in Fig. 2a. The Z basis measurements project the region into eigenstates of the Z stabilizers. Second, the syndrome qubits across the entire lattice are interacted with their neighboring data qubits as shown in Fig. 2b. Third, the measurement pattern shown in Fig. 2c completes one round of stabilizer measurement. The interaction pattern of Fig. 2b is executed a total of d times, interleaved with the measurement pattern of Fig. 2c. Finally, after the d th round of interaction, the measurement pattern shown in Fig. 2d is applied, completing the fault-tolerant movement of the logical qubit.

All measurement results are simply sent to the destination end of the lattice, not processed during transmission. The final round of measurements prepares the lattice for the transmission of the next logical qubit. Assuming each interacting quantum gate takes T_g seconds and each measurement T_m seconds, a logical qubit can be transmitted every $(4T_g + T_m)d$ seconds. The scaling of d and values required for practical communication will be discussed later after the full communication scheme has been described.




FIG. 2: Monolithic surface code quantum communication. a.) Monolithic lattice of qubits with source logical qubit $|\Psi_L\rangle$, initial measurement pattern for the intermediate region, and destination area initialized to $|0_L\rangle$. b.) Circuits used in parallel to prepare for stabilizer measurement. Numbers indicate the timing of gates. c.) Intermediate stabilizer measurements. d.) Final stabilizer measurement and communicated state.

The processing of measurement results related to X and Z stabilizers occurs independently. Errors result in stabilizer measurements changing. A chain of errors leads to changes in the stabilizer measurements only at the endpoints of the chain. A good approximation of the most likely pattern of errors corresponding to a given set of stabilizer measurement changes is one in which every change is connected by a chain of errors to another change or lattice boundary such that the total number of errors is a minimum. A classical algorithm, the minimum weight perfect matching algorithm [21], can find such a pattern efficiently, in time growing poly-logarithmically with the volume of the lattice when parallel processing is used [22]. An alternative algorithm with similar runtime has been devised recently [23]. Error correction fails when the corrections actually create error chains connecting pairs of opposing boundaries. With careful calculation of the distance between changes, a minimum of $\lfloor (d+1)/2 \rfloor$ errors must occur before failure is possible, implying p_c decreases exponentially with d .

When communicating over a large physical distance,




FIG. 3: Repeater-based surface code quantum communication. The qubit pattern in each quantum repeater (ellipses) is for $d = 3$. The pattern width is independent of d .




FIG. 4: If the probability of heralded success is sufficiently high, qubit A can be interacted with its neighboring data qubits and measured before the entangling pulse/photon even reaches its destination. Error correction takes care of heralded failures, including loss during transmission.

the fundamental entanglement resource is expected to be Bell pairs created over fiber links kilometers in length. The monolithic lattice described above can be broken into pieces connected by Bell pairs as shown in Fig. 3. Stabilizers spanning the communication link can be measured using the approach shown in Fig. 4. We temporarily ignore heralded failure to entangle, which is discussed below. The left half of each Bell pair can be measured before the right half even reaches its destination. The rate of the scheme thus remains unchanged — one logical qubit every $(4T_g + T_m)d$ seconds. Latency is, however, introduced as the qubits in any given repeater station are not initialized until the first photons arrive from the left. For many ranges of parameters, a given repeater will have finished working and sending photons before the next repeater receives its first photons.

The scheme's maximum tolerable Bell pair error rate is of critical importance. Let us temporarily assume that all gates within repeater nodes are perfect and Bell pairs are subject to depolarizing errors. We shall continue to ignore heralded failure to entangle for the moment. A probability p_B of depolarizing error on a Bell pair means that the errors $IX, IY, IZ, XI, XX, XY, XZ, YI, YX, YY, YZ, ZI, ZX, ZY, ZZ$ each occur with probability $p_B/15$. Using the Bell pair stabilizers XX and ZZ , these errors are equivalent to II with probability $p_B/5$ and IX, IY, IZ with equal probability $4p_B/15$.

After correction, nontrivial combinations of X/Z errors form a chain that runs from the top spatial/temporal




FIG. 5: Average number of error correction rounds before logical failure versus Bell pair error rate p_B and code distance.

boundary to the bottom spatial/temporal boundary. Given this symmetry, and the fact that the different types of errors are processed independently, we focus on IX errors, which occur on any given Bell pair with probability $p_X = 8p_B/15$. Referring to the Bell pairs numbered 1 to $2d-1$ in Fig. 3, IX errors on odd pairs induce an X error on the data qubit to their left whereas on even pairs the result is an incorrect stabilizer measurement.

These errors can be visualized as the bonds of a $d \times t$ 2-D square lattice. The error rate p_X is too high when, after correction, the probability of having a chain of errors along the d dimension increases with d . For $t = 1$, we have a repetition code, implying $p_X < 0.5$ is correctable. For $t = d$, we have a surface code with perfect syndrome measurement implying $p_X \lesssim 0.1$ [14]. The equivalent values of p_B are $15/16$ and approximately 0.2.

We simulated a pair of repeater nodes with perfect gates and depolarized Bell pairs for verification (Fig. 5). Note the expected crossover at $p_B = 15/16 \sim 0.94$. Significant growth of the time to failure with d occurs for $p_B \lesssim 0.2$, as expected. Rapid growth occurs for $p_B \sim 0.1$, equivalent to a fidelity F of the entangled state ρ with respect to the desired Bell state $|\Phi^+\rangle$ of 0.92 since $F = \langle \Phi^+ | \rho | \Phi^+ \rangle = 1 - 4p/5$ for Bell pairs corrupted by depolarizing errors.

Loss during transmission can be modeled as measurement in an unknown basis. Loss is easier to tolerate than depolarizing noise as the failure to measure the transmitted pulse or photon gives the location of the error. This can be seen in the simulation results of Fig. 6, which shows efficient handling of 40-45% loss. Note that no code can handle more than 50% loss as this would violate the no-cloning theorem [1, 2].

The probability of logical error after d successful stabilizer measurements, p_{link} , is shown in Fig. 7 versus p_B and loss p_L . For 35% loss and 5% error ($F = 0.96$), increasing d by 30 decreases p_{link} by a factor of 10. Send-




FIG. 6: Average number of error correction rounds before logical failure versus loss and code distance.




FIG. 7: Probability of logical error per link for a variety of loss and Bell error rates.

ing data through 10^4 repeaters with 10^{-6} error would require $d \sim 300$, corresponding to of order a thousand qubits per repeater. Each repeater takes time $d(4T_g + T_m)/(1 - p_L)$ to send a logical qubit. Long-range, high fidelity MHz communication can thus be achieved provided $300(4T_g + T_m)/0.65 \sim 1\mu s$, meaning $\sim 2ns$ gates.

Permitting repeaters to have a nonzero local gate error rate p_g will only have significant impact if it is close to the threshold error rate of approximately $p_g^{th} = 0.75\%$ [16]. An error rate one or two orders of magnitude below this will not significantly change the above results.

To summarize, we have shown that, provided the Bell pair error rate is less than approximately 10% ($F \gtrsim 0.92$), utilizing surface code quantum error correction enables the practical fault-tolerant quantum communication of logical qubits over an arbitrary number of links N with arbitrarily low communication error rate p_c given $O(\log N/p_c)$ qubits per repeater. If the rate of loss is high, the communication time is proportional to the time T_B required to successfully create a Bell pair and the

number of Bell pairs per link $O(\log^2 N/p_c)$. If the loss is below approximately 35% and $F \gtrsim 0.96$, no heralding is required and of order a thousand qubits per repeater and nanosecond gates enables one to send logical qubits at a MHz rate with 10^{-6} error through 10^4 links — sufficient in principle to reach the opposite side of the planet.

We acknowledge helpful discussions with Bill Munro, Simon Devitt, Ashley Stephens and Sean Barrett. AGF, DSW, CDH, LLCH acknowledge support from the Australian Research Council, the Australian Government, and the US National Security Agency (NSA) and the Army Research Office (ARO) under contract number W911NF-08-1-0527. RV acknowledges support from JSPS. TDL was partially supported by the National Science Foundation CCR-08 29694, MEXT, and NICT.

-
- [1] D. Dieks, Phys. Lett. A **92**, 271 (1982).
 - [2] W. K. Wootters and W. H. Zurek, Nature **299**, 802 (1982).
 - [3] H.-J. Briegel, W. Dür, J. I. Cirac, and P. Zoller, Phys. Rev. Lett. **81**, 5932 (1998).
 - [4] C. H. Bennett et al., Phys. Rev. Lett. **76**, 722 (1996).
 - [5] M. Zukowski, A. Zeilinger, M. A. Horne, and A. K. Ekert, Phys. Rev. Lett. **71**, 4287 (1993).
 - [6] N. Sangouard, C. Simon, H. de Riedmatten, and N. Gisin, arXiv:0906.2699 (2009).
 - [7] S. Perseguers, L. Jiang, N. Schuch, F. Verstraete, M. D. Lukin, J. I. Cirac, and K. G. H. Vollbrecht, Phys. Rev. A **78**, 062324 (2008), arXiv:0807.0208.
 - [8] S. Perseguers, arXiv:0910.1459 (2009).
 - [9] L. Jiang, J. M. Taylor, K. Nemoto, W. J. Munro, R. Van Meter, and M. D. Lukin, Phys. Rev. A **79**, 032325 (2009).
 - [10] W. J. Munro, K. A. Harrison, A. Stephens, S. Devitt, and K. Nemoto (2009), arXiv:0910.4038.
 - [11] S. B. Bravyi and A. Y. Kitaev, quant-ph/9811052 (1998).
 - [12] E. Dennis, A. Kitaev, A. Landahl, and J. Preskill, J. Math. Phys. **43**, 4452 (2002), quant-ph/0110143.
 - [13] A. G. Fowler, A. M. Stephens, and P. Groszkowski, Phys. Rev. A **80**, 052312 (2009), arXiv:0803.0272.
 - [14] D. S. Wang, A. G. Fowler, A. M. Stephens, and L. C. L. Hollenberg, arXiv:0905.0531 (2009).
 - [15] D. Gottesman, Ph.D. thesis, Caltech (1997), quant-ph/9705052.
 - [16] R. Raussendorf and J. Harrington, Phys. Rev. Lett. **98**, 190504 (2007), quant-ph/0610082.
 - [17] T. M. Stace, S. D. Barrett, and A. C. Doherty, Phys. Rev. Lett. **102**, 200501 (2009), arXiv:0904.3556.
 - [18] R. Van Meter, T. D. Ladd, A. G. Fowler, and Y. Yamamoto, International Journal of Quantum Information (2010), to appear; preprint arXiv:0906.2686.
 - [19] D. P. DiVincenzo, arXiv:0905.4839 (2009), nobel Symposium on Qubits for Quantum Information.
 - [20] J. M. Aminiz et al., arXiv:0909.2464 (2009).
 - [21] W. Cook and A. Rohe, INFORMS J. Comput. **11**, 138 (1999).
 - [22] S. J. Devitt, A. G. Fowler, T. Tilma, W. J. Munro, and K. Nemoto, arXiv:0906.0415 (2009).
 - [23] G. Duclos-Cianci and D. Poulin, arXiv:0911.0581 (2009).